

RDC

Generated by Doxygen 1.8.5

Tue Apr 26 2022 00:56:17

Contents

1	Data Structure Index	1
1.1	Data Structures	1
2	File Index	3
2.1	File List	3
3	Data Structure Documentation	5
3.1	rdc_device_attributes_t Struct Reference	5
3.1.1	Detailed Description	5
3.2	rdc_diag_detail_t Struct Reference	5
3.2.1	Detailed Description	5
3.3	rdc_diag_per_gpu_result_t Struct Reference	6
3.3.1	Detailed Description	6
3.4	rdc_diag_response_t Struct Reference	6
3.4.1	Detailed Description	6
3.5	rdc_diag_test_result_t Struct Reference	6
3.5.1	Detailed Description	7
3.5.2	Field Documentation	7
3.5.2.1	per_gpu_result_count	7
3.6	rdc_field_group_info_t Struct Reference	7
3.6.1	Detailed Description	7
3.6.2	Field Documentation	8
3.6.2.1	field_ids	8
3.7	rdc_field_value Struct Reference	8
3.7.1	Detailed Description	8
3.7.2	Field Documentation	8
3.7.2.1	value	8
3.8	rdc_field_value_data Union Reference	8
3.8.1	Detailed Description	9
3.9	rdc_gpu_usage_info_t Struct Reference	9
3.9.1	Detailed Description	9
3.10	rdc_group_info_t Struct Reference	10

3.10.1	Detailed Description	10
3.10.2	Field Documentation	10
3.10.2.1	entity_ids	10
3.11	rdc_job_group_info_t Struct Reference	10
3.11.1	Detailed Description	10
3.12	rdc_job_info_t Struct Reference	11
3.12.1	Detailed Description	11
3.12.2	Field Documentation	11
3.12.2.1	summary	11
3.13	rdc_stats_summary_t Struct Reference	11
3.13.1	Detailed Description	11
4	File Documentation	13
4.1	rdc.h File Reference	13
4.1.1	Detailed Description	17
4.1.2	Typedef Documentation	17
4.1.2.1	rdc_handle_t	17
4.1.3	Enumeration Type Documentation	18
4.1.3.1	rdc_status_t	18
4.1.3.2	rdc_group_type_t	18
4.1.3.3	rdc_field_t	18
4.1.3.4	rdc_diag_level_t	20
4.1.3.5	rdc_diag_result_t	20
4.1.3.6	rdc_diag_test_cases_t	20
4.1.4	Function Documentation	20
4.1.4.1	rdc_init	20
4.1.4.2	rdc_shutdown	21
4.1.4.3	rdc_start_embedded	21
4.1.4.4	rdc_stop_embedded	21
4.1.4.5	rdc_connect	21
4.1.4.6	rdc_disconnect	22
4.1.4.7	rdc_job_start_stats	22
4.1.4.8	rdc_job_get_stats	22
4.1.4.9	rdc_job_stop_stats	23
4.1.4.10	rdc_job_remove	23
4.1.4.11	rdc_job_remove_all	23
4.1.4.12	rdc_field_update_all	24
4.1.4.13	rdc_device_get_all	24
4.1.4.14	rdc_device_get_attributes	24
4.1.4.15	rdc_group_gpu_create	24

4.1.4.16	rdc_group_gpu_add	25
4.1.4.17	rdc_group_gpu_get_info	25
4.1.4.18	rdc_group_get_all_ids	25
4.1.4.19	rdc_group_gpu_destroy	26
4.1.4.20	rdc_group_field_create	26
4.1.4.21	rdc_group_field_get_info	26
4.1.4.22	rdc_group_field_get_all_ids	27
4.1.4.23	rdc_group_field_destroy	27
4.1.4.24	rdc_field_watch	27
4.1.4.25	rdc_field_get_latest_value	28
4.1.4.26	rdc_field_get_value_since	28
4.1.4.27	rdc_field_unwatch	28
4.1.4.28	rdc_diagnostic_run	29
4.1.4.29	rdc_test_case_run	29
4.1.4.30	rdc_status_string	29
4.1.4.31	field_id_string	30
4.1.4.32	get_field_id_from_name	30
4.1.4.33	rdc_diagnostic_result_string	30

Index**31**

Chapter 1

Data Structure Index

1.1 Data Structures

Here are the data structures with brief descriptions:

rdc_device_attributes_t	Represents attributes corresponding to a device	5
rdc_diag_detail_t	Details of the diagnostic errors	5
rdc_diag_per_gpu_result_t	Details of the per gpu diagnostic results	6
rdc_diag_response_t	The diagnostic responses for test cases	6
rdc_diag_test_result_t	The diagnostic results for all GPUs	6
rdc_field_group_info_t	The structure to store the field group info	7
rdc_field_value	The structure to store the field value	8
rdc_field_value_data	Field value data	8
rdc_gpu_usage_info_t	The structure to hold the GPU usage information	9
rdc_group_info_t	The structure to store the group info	10
rdc_job_group_info_t	The structure to store the job info	10
rdc_job_info_t	The structure to hold the job stats	11
rdc_stats_summary_t	The structure to store summary of data	11

Chapter 2

File Index

2.1 File List

Here is a list of all documented files with brief descriptions:

[rdc.h](#)

The rocm_rdc library api is new, and therefore subject to change either at the ABI or API level. Instead of marking every function prototype as "unstable", we are instead saying the API is unstable (i.e., changes are possible) while the major version remains 0. This means that if the API/ABI changes, we will not increment the major version to 1. Once the ABI stabilizes, we will increment the major version to 1, and thereafter increment it on all ABI breaks

13

Chapter 3

Data Structure Documentation

3.1 rdc_device_attributes_t Struct Reference

Represents attributes corresponding to a device.

```
#include <rdc.h>
```

Data Fields

- char [device_name](#) [[RDC_MAX_STR_LENGTH](#)]
Name of the device.

3.1.1 Detailed Description

Represents attributes corresponding to a device.

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.2 rdc_diag_detail_t Struct Reference

details of the diagnostic errors

```
#include <rdc.h>
```

Data Fields

- char [msg](#) [[MAX_DIAG_MSG_LENGTH](#)]
The test result details.
- uint32_t [code](#)
The low level error code.

3.2.1 Detailed Description

details of the diagnostic errors

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.3 rdc_diag_per_gpu_result_t Struct Reference

details of the per gpu diagnostic results

```
#include <rdc.h>
```

Data Fields

- [uint32_t gpu_index](#)
The GPU index.
- [rdc_diag_detail_t gpu_result](#)
The detail results.

3.3.1 Detailed Description

details of the per gpu diagnostic results

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.4 rdc_diag_response_t Struct Reference

The diagnostic responses for test cases.

```
#include <rdc.h>
```

Data Fields

- [uint32_t results_count](#)
- [rdc_diag_test_result_t diag_info](#) [[MAX_TEST_CASES](#)]

3.4.1 Detailed Description

The diagnostic responses for test cases.

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.5 rdc_diag_test_result_t Struct Reference

The diagnostic results for all GPUs.

```
#include <rdc.h>
```

Data Fields

- [rdc_diag_result_t status](#)
The diagnostic result.
- [rdc_diag_detail_t details](#)
The summary details.
- [rdc_diag_test_cases_t test_case](#)
The test case to run.
- `uint32_t` [per_gpu_result_count](#)
Result details.
- [rdc_diag_per_gpu_result_t gpu_results](#) [RDC_MAX_NUM_DEVICES]
- `char` [info](#) [MAX_DIAG_MSG_LENGTH]
Detail information.

3.5.1 Detailed Description

The diagnostic results for all GPUs.

3.5.2 Field Documentation

3.5.2.1 `uint32_t rdc_diag_test_result_t::per_gpu_result_count`

Result details.

How many `gpu_results`

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.6 rdc_field_group_info_t Struct Reference

The structure to store the field group info.

```
#include <rdc.h>
```

Data Fields

- `uint32_t` [count](#)
count of fields in the group
- `char` [group_name](#) [RDC_MAX_STR_LENGTH]
field group name
- [rdc_field_t field_ids](#) [RDC_MAX_FIELD_IDS_PER_FIELD_GROUP]

3.6.1 Detailed Description

The structure to store the field group info.

3.6.2 Field Documentation

3.6.2.1 `rdc_field_t rdc_field_group_info_t::field_ids[RDC_MAX_FIELD_IDS_PER_FIELD_GROUP]`

The list of fields in the group

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.7 `rdc_field_value` Struct Reference

The structure to store the field value.

```
#include <rdc.h>
```

Data Fields

- [rdc_field_t field_id](#)
The field id of the value.
- `int` [status](#)
RDC_ST_OK or error status.
- `uint64_t` [ts](#)
Timestamp in usec since 1970.
- [rdc_field_type_t](#) `type`
The field type.
- [rdc_field_value_data](#) `value`

3.7.1 Detailed Description

The structure to store the field value.

3.7.2 Field Documentation

3.7.2.1 `rdc_field_value_data rdc_field_value::value`

Value of the field. Value type depends on the field type.

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.8 `rdc_field_value_data` Union Reference

Field value data.

```
#include <rdc.h>
```

Data Fields

- `int64_t` [l_int](#)
- `double` [dbl](#)
- `char` [str](#) [[RDC_MAX_STR_LENGTH](#)]

3.8.1 Detailed Description

Field value data.

The documentation for this union was generated from the following file:

- [rdc.h](#)

3.9 rdc_gpu_usage_info_t Struct Reference

The structure to hold the GPU usage information.

```
#include <rdc.h>
```

Data Fields

- `uint32_t` [gpu_id](#)
GPU_ID_INVALID for summary information.
- `uint64_t` [start_time](#)
The time to start the watching.
- `uint64_t` [end_time](#)
The time to stop the watching.
- `uint64_t` [energy_consumed](#)
GPU Energy consumed.
- `uint64_t` [ecc_correct](#)
Correctable errors.
- `uint64_t` [ecc_uncorrect](#)
Uncorrrtable errors.
- `rdc_stats_summary_t` [pcie_tx](#)
Bytes sent over PCIe stats.
- `rdc_stats_summary_t` [pcie_rx](#)
Bytes received over PCIe stats.
- `rdc_stats_summary_t` [power_usage](#)
GPU Power usage stats.
- `rdc_stats_summary_t` [gpu_clock](#)
GPU Clock speed stats.
- `rdc_stats_summary_t` [memory_clock](#)
Mem. Clock speed stats.
- `rdc_stats_summary_t` [gpu_utilization](#)
GPU Utilization stats.
- `rdc_stats_summary_t` [gpu_temperature](#)
GPU temperature stats.
- `uint64_t` [max_gpu_memory_used](#)
Maximum GPU memory used.
- `rdc_stats_summary_t` [memory_utilization](#)
Memory Utilization statistics.

3.9.1 Detailed Description

The structure to hold the GPU usage information.

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.10 rdc_group_info_t Struct Reference

The structure to store the group info.

```
#include <rdc.h>
```

Data Fields

- unsigned int [count](#)
count of GPUs in the group
- char [group_name](#) [RDC_MAX_STR_LENGTH]
group name
- uint32_t [entity_ids](#) [RDC_GROUP_MAX_ENTITIES]

3.10.1 Detailed Description

The structure to store the group info.

3.10.2 Field Documentation

3.10.2.1 uint32_t rdc_group_info_t::entity_ids[RDC_GROUP_MAX_ENTITIES]

The list of entities in the group

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.11 rdc_job_group_info_t Struct Reference

The structure to store the job info.

```
#include <rdc.h>
```

Data Fields

- char [job_id](#) [RDC_MAX_STR_LENGTH]
job id
- [rdc_gpu_group_t](#) [group_id](#)
group name
- uint64_t [start_time](#)
job start time
- uint64_t [stop_time](#)
job stop time

3.11.1 Detailed Description

The structure to store the job info.

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.12 rdc_job_info_t Struct Reference

The structure to hold the job stats.

```
#include <rdc.h>
```

Data Fields

- [uint32_t num_gpus](#)
Number of GPUs used by job.
- [rdc_gpu_usage_info_t summary](#)
- [rdc_gpu_usage_info_t gpus](#) [16]
Job usage summary statistics by GPU.

3.12.1 Detailed Description

The structure to hold the job stats.

3.12.2 Field Documentation

3.12.2.1 [rdc_gpu_usage_info_t rdc_job_info_t::summary](#)

Job usage summary statistics (overall)

The documentation for this struct was generated from the following file:

- [rdc.h](#)

3.13 rdc_stats_summary_t Struct Reference

The structure to store summary of data.

```
#include <rdc.h>
```

Data Fields

- [uint64_t max_value](#)
Maximum value measured.
- [uint64_t min_value](#)
Minimum value measured.
- [uint64_t average](#)
Average value measured.
- [double standard_deviation](#)
The standard deviation.

3.13.1 Detailed Description

The structure to store summary of data.

The documentation for this struct was generated from the following file:

- [rdc.h](#)

Chapter 4

File Documentation

4.1 rdc.h File Reference

The rocm_rdc library api is new, and therefore subject to change either at the ABI or API level. Instead of marking every function prototype as "unstable", we are instead saying the API is unstable (i.e., changes are possible) while the major version remains 0. This means that if the API/ABI changes, we will not increment the major version to 1. Once the ABI stabilizes, we will increment the major version to 1, and thereafter increment it on all ABI breaks.

```
#include <stdint.h>
```

Data Structures

- struct [rdc_device_attributes_t](#)
Represents attributes corresponding to a device.
- struct [rdc_group_info_t](#)
The structure to store the group info.
- struct [rdc_stats_summary_t](#)
The structure to store summary of data.
- struct [rdc_gpu_usage_info_t](#)
The structure to hold the GPU usage information.
- struct [rdc_job_info_t](#)
The structure to hold the job stats.
- union [rdc_field_value_data](#)
Field value data.
- struct [rdc_field_value](#)
The structure to store the field value.
- struct [rdc_field_group_info_t](#)
The structure to store the field group info.
- struct [rdc_job_group_info_t](#)
The structure to store the job info.
- struct [rdc_diag_detail_t](#)
details of the diagnostic errors
- struct [rdc_diag_per_gpu_result_t](#)
details of the per gpu diagnostic results
- struct [rdc_diag_test_result_t](#)
The diagnostic results for all GPUs.
- struct [rdc_diag_response_t](#)
The diagnostic responses for test cases.

Macros

- `#define GPU_ID_INVALID -1`
ID used to represent an invalid GPU.
- `#define RDC_GROUP_ALL_GPUS -1000`
Used to specify all GPUs.
- `#define RDC_JOB_STATS_FIELDS -1000`
Used to specify all stats fields.
- `#define RDC_MAX_STR_LENGTH 256`
The max rdc field string length.
- `#define RDC_GROUP_MAX_ENTITIES 64`
The max entities in a group.
- `#define RDC_MAX_NUM_DEVICES 16`
Max number of GPUs supported by RDC.
- `#define RDC_MAX_FIELD_IDS_PER_FIELD_GROUP 128`
The max fields in a field group.
- `#define RDC_MAX_NUM_GROUPS 64`
The max number of groups.
- `#define RDC_MAX_NUM_FIELD_GROUPS 64`
The max number of the field groups.
- `#define RDC_EVT_IS_NOTIF_FIELD(FIELD) ((FIELD) >= RDC_EVT_NOTIF_FIRST && (FIELD) <= RDC_EVT_NOTIF_LAST)`
- `#define MAX_DIAG_MSG_LENGTH 4096`
The maximum length of the diagnostic messages.

Typedefs

- `typedef void * rdc_handle_t`
handlers used in various rdc calls
- `typedef uint32_t rdc_gpu_group_t`
GPU Group ID type.
- `typedef uint32_t rdc_field_grp_t`
Field group ID type.

Enumerations

- `enum rdc_status_t {`
`RDC_ST_OK = 0, RDC_ST_NOT_SUPPORTED, RDC_ST_MSI_ERROR, RDC_ST_FAIL_LOAD_MODULE,`
`RDC_ST_INVALID_HANDLER, RDC_ST_BAD_PARAMETER, RDC_ST_NOT_FOUND, RDC_ST_CONFLICT,`
`RDC_ST_CLIENT_ERROR, RDC_ST_ALREADY_EXIST, RDC_ST_MAX_LIMIT, RDC_ST_INSUFF_RESOURCES,`
`RDC_ST_FILE_ERROR, RDC_ST_NO_DATA, RDC_ST_PERM_ERROR, RDC_ST_UNKNOWN_ERROR`
`= 0xFFFFFFFF }`
Error codes returned by rocm_rdc_lib functions.
- `enum rdc_operation_mode_t { RDC_OPERATION_MODE_AUTO = 0, RDC_OPERATION_MODE_MANUAL }`
rdc operation mode rdc can run in auto mode where background threads will collect metrics. When run in manual mode, the user needs to periodically call rdc_field_update_all for data collection.
- `enum rdc_group_type_t { RDC_GROUP_DEFAULT = 0, RDC_GROUP_EMPTY }`
type of GPU group

- enum `rdc_field_type_t` { **INTEGER** = 0, **DOUBLE**, **STRING**, **BLOB** }
the type stored in the filed value
- enum `rdc_field_t` {
`RDC_FI_INVALID` = 0, `RDC_FI_GPU_COUNT` = 1, `RDC_FI_DEV_NAME`, `RDC_FI_GPU_CLOCK` = 100,
`RDC_FI_MEM_CLOCK`, `RDC_FI_MEMORY_TEMP` = 200, `RDC_FI_GPU_TEMP`, `RDC_FI_POWER_USAGE` = 300,
`RDC_FI_PCIE_TX` = 400, `RDC_FI_PCIE_RX`, `RDC_FI_GPU_UTIL` = 500, `RDC_FI_GPU_MEMORY_USAGE`,
`RDC_FI_GPU_MEMORY_TOTAL`, `RDC_FI_ECC_CORRECT_TOTAL` = 600, `RDC_FI_ECC_UNCORRECT_TOTAL`, `RDC_FI_ECC_SDMA_SEC`,
`RDC_FI_ECC_SDMA_DED`, `RDC_FI_ECC_GFX_SEC`, `RDC_FI_ECC_GFX_DED`, `RDC_FI_ECC_MMHUB_SEC`,
`RDC_FI_ECC_MMHUB_DED`, `RDC_FI_ECC_ATHUB_SEC`, `RDC_FI_ECC_ATHUB_DED`, `RDC_FI_ECC_BIF_SEC`,
`RDC_FI_ECC_BIF_DED`, `RDC_FI_ECC_HDP_SEC`, `RDC_FI_ECC_HDP_DED`, `RDC_FI_ECC_XGMI_WAFL_SEC`,
`RDC_FI_ECC_XGMI_WAFL_DED`, `RDC_FI_ECC_DF_SEC`, `RDC_FI_ECC_DF_DED`, `RDC_FI_ECC_SMN_SEC`,
`RDC_FI_ECC_SMN_DED`, `RDC_FI_ECC_SEM_SEC`, `RDC_FI_ECC_SEM_DED`, `RDC_FI_ECC_MP0_SEC`,
`RDC_FI_ECC_MP0_DED`, `RDC_FI_ECC_MP1_SEC`, `RDC_FI_ECC_MP1_DED`, `RDC_FI_ECC_FUSE_SEC`,
`RDC_FI_ECC_FUSE_DED`, `RDC_FI_ECC_UMC_SEC`, `RDC_FI_ECC_UMC_DED`, `RDC_EVNT_XGMI_0_NOP_TX` = 1000,
`RDC_EVNT_XGMI_0_REQ_TX`, `RDC_EVNT_XGMI_0_RESP_TX`, `RDC_EVNT_XGMI_0_BEATS_TX`, `RDC_EVNT_XGMI_1_NOP_TX`,
`RDC_EVNT_XGMI_1_REQ_TX`, `RDC_EVNT_XGMI_1_RESP_TX`, `RDC_EVNT_XGMI_1_BEATS_TX`, `RDC_EVNT_XGMI_0_THRPUT` = 1500,
`RDC_EVNT_XGMI_1_THRPUT`, `RDC_EVNT_XGMI_2_THRPUT`, `RDC_EVNT_XGMI_3_THRPUT`, `RDC_EVNT_XGMI_4_THRPUT`,
`RDC_EVNT_XGMI_5_THRPUT`, `RDC_EVNT_NOTIF_VMFAULT` = 2000, **`RDC_EVNT_NOTIF_FIRST`** = `RDC_EVNT_NOTIF_VMFAULT`, `RDC_EVNT_NOTIF_THERMAL_THROTTLE`,
`RDC_EVNT_NOTIF_PRE_RESET`, `RDC_EVNT_NOTIF_POST_RESET`, **`RDC_EVNT_NOTIF_LAST`** = `RDC_EVNT_NOTIF_POST_RESET` }
type of diagnostic level
- enum `rdc_diag_level_t` { `RDC_DIAG_LVL_INVALID` = 0, `RDC_DIAG_LVL_SHORT`, `RDC_DIAG_LVL_MED`, `RDC_DIAG_LVL_LONG` }
type of diagnostic result
- enum `rdc_diag_result_t` { `RDC_DIAG_RESULT_PASS`, `RDC_DIAG_RESULT_SKIP`, `RDC_DIAG_RESULT_WARN`, `RDC_DIAG_RESULT_FAIL` }
type of diagnostic result
- enum `rdc_diag_test_cases_t` {
`RDC_DIAG_TEST_FIRST` = 0, **`RDC_DIAG_COMPUTE_PROCESS`** = `RDC_DIAG_TEST_FIRST`, `RDC_DIAG_COMPUTE_QUEUE`, `RDC_DIAG_SYS_MEM_CHECK`,
`RDC_DIAG_NODE_TOPOLOGY`, `RDC_DIAG_GPU_PARAMETERS`, **`RDC_DIAG_TEST_LAST`** = `RDC_DIAG_GPU_PARAMETERS` }
The test cases to run.

Functions

- `rdc_status_t rdc_init` (uint64_t init_flags)
Initialize ROCm RDC.
- `rdc_status_t rdc_shutdown` ()
Shutdown ROCm RDC.
- `rdc_status_t rdc_start_embedded` (rdc_operation_mode_t op_mode, rdc_handle_t *p_rdc_handle)
Start embedded RDC agent within this process.

- [rdc_status_t rdc_stop_embedded](#) ([rdc_handle_t](#) p_rdc_handle)
Stop embedded RDC agent.
- [rdc_status_t rdc_connect](#) (const char *ipAndPort, [rdc_handle_t](#) *p_rdc_handle, const char *root_ca, const char *client_cert, const char *client_key)
Connect to rdcd daemon.
- [rdc_status_t rdc_disconnect](#) ([rdc_handle_t](#) p_rdc_handle)
Disconnect from rdcd daemon.
- [rdc_status_t rdc_job_start_stats](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_gpu_group_t](#) group_id, const char job_id[64], [uint64_t](#) update_freq)
Request the RDC to watch the job stats.
- [rdc_status_t rdc_job_get_stats](#) ([rdc_handle_t](#) p_rdc_handle, const char job_id[64], [rdc_job_info_t](#) *p_job_info)
Get the stats of the job using the job id.
- [rdc_status_t rdc_job_stop_stats](#) ([rdc_handle_t](#) p_rdc_handle, const char job_id[64])
Request RDC to stop watching the stats of the job.
- [rdc_status_t rdc_job_remove](#) ([rdc_handle_t](#) p_rdc_handle, const char job_id[64])
Request RDC to stop tracking the job given by job_id.
- [rdc_status_t rdc_job_remove_all](#) ([rdc_handle_t](#) p_rdc_handle)
Request RDC to stop tracking all the jobs.
- [rdc_status_t rdc_field_update_all](#) ([rdc_handle_t](#) p_rdc_handle, [uint32_t](#) wait_for_update)
Request RDC to update all fields to be watched.
- [rdc_status_t rdc_device_get_all](#) ([rdc_handle_t](#) p_rdc_handle, [uint32_t](#) gpu_index_list[RDC_MAX_NUM_DEVICES], [uint32_t](#) *count)
Get indexes corresponding to all the devices on the system.
- [rdc_status_t rdc_device_get_attributes](#) ([rdc_handle_t](#) p_rdc_handle, [uint32_t](#) gpu_index, [rdc_device_attributes_t](#) *p_rdc_attr)
Gets device attributes corresponding to the gpu_index.
- [rdc_status_t rdc_group_gpu_create](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_group_type_t](#) type, const char *group_name, [rdc_gpu_group_t](#) *p_rdc_group_id)
Create a group contains multiple GPUs.
- [rdc_status_t rdc_group_gpu_add](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_gpu_group_t](#) group_id, [uint32_t](#) gpu_index)
Add a GPU to the group.
- [rdc_status_t rdc_group_gpu_get_info](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_gpu_group_t](#) p_rdc_group_id, [rdc_group_info_t](#) *p_rdc_group_info)
Get information about a GPU group.
- [rdc_status_t rdc_group_get_all_ids](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_gpu_group_t](#) group_id_list[], [uint32_t](#) *count)
Used to get information about all GPU groups in the system.
- [rdc_status_t rdc_group_gpu_destroy](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_gpu_group_t](#) p_rdc_group_id)
Destroy GPU group represented by p_rdc_group_id.
- [rdc_status_t rdc_group_field_create](#) ([rdc_handle_t](#) p_rdc_handle, [uint32_t](#) num_field_ids, [rdc_field_t](#) *field_ids, const char *field_group_name, [rdc_field_grp_t](#) *rdc_field_group_id)
create a group of fields
- [rdc_status_t rdc_group_field_get_info](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_field_grp_t](#) rdc_field_group_id, [rdc_field_group_info_t](#) *field_group_info)
Get information about a field group.
- [rdc_status_t rdc_group_field_get_all_ids](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_field_grp_t](#) field_group_id_list[], [uint32_t](#) *count)
Used to get information about all field groups in the system.
- [rdc_status_t rdc_group_field_destroy](#) ([rdc_handle_t](#) p_rdc_handle, [rdc_field_grp_t](#) rdc_field_group_id)
Destroy field group represented by rdc_field_group_id.

- `rdc_status_t rdc_field_watch` (`rdc_handle_t` p_rdc_handle, `rdc_gpu_group_t` group_id, `rdc_field_grp_t` field_group_id, `uint64_t` update_freq, `double` max_keep_age, `uint32_t` max_keep_samples)
Request the RDC start recording updates for a given field collection.
- `rdc_status_t rdc_field_get_latest_value` (`rdc_handle_t` p_rdc_handle, `uint32_t` gpu_index, `rdc_field_t` field, `rdc_field_value_t` *value)
Request a latest cached field of a GPU.
- `rdc_status_t rdc_field_get_value_since` (`rdc_handle_t` p_rdc_handle, `uint32_t` gpu_index, `rdc_field_t` field, `uint64_t` since_time_stamp, `uint64_t` *next_since_time_stamp, `rdc_field_value_t` *value)
Request a history cached field of a GPU.
- `rdc_status_t rdc_field_unwatch` (`rdc_handle_t` p_rdc_handle, `rdc_gpu_group_t` group_id, `rdc_field_grp_t` field_group_id)
Stop record updates for a given field collection.
- `rdc_status_t rdc_diagnostic_run` (`rdc_handle_t` p_rdc_handle, `rdc_gpu_group_t` group_id, `rdc_diag_level_t` level, `rdc_diag_response_t` *response)
Run the diagnostic test cases.
- `rdc_status_t rdc_test_case_run` (`rdc_handle_t` p_rdc_handle, `rdc_gpu_group_t` group_id, `rdc_diag_test_cases_t` test_case, `rdc_diag_test_result_t` *result)
Run one diagnostic test case.
- `const char * rdc_status_string` (`rdc_status_t` status)
Get a description of a provided RDC error status.
- `const char * field_id_string` (`rdc_field_t` field_id)
Get the name of a field.
- `rdc_field_t get_field_id_from_name` (`const char *`name)
Get the field id from name.
- `const char * rdc_diagnostic_result_string` (`rdc_diag_result_t` result)
Get a description of a diagnostic result.

Variables

- `const uint32_t MAX_TEST_CASES` = `RDC_DIAG_TEST_LAST` - `RDC_DIAG_TEST_FIRST` + 1
The maximum test cases to run.

4.1.1 Detailed Description

The rocm_rdc library api is new, and therefore subject to change either at the ABI or API level. Instead of marking every function prototype as "unstable", we are instead saying the API is unstable (i.e., changes are possible) while the major version remains 0. This means that if the API/ABI changes, we will not increment the major version to 1. Once the ABI stabilizes, we will increment the major version to 1, and thereafter increment it on all ABI breaks. Main header file for the ROCm RDC library. All required function, structure, enum, etc. definitions should be defined in this file.

4.1.2 Typedef Documentation

4.1.2.1 typedef void* rdc_handle_t

handlers used in various rdc calls

Handle used for an RDC session

4.1.3 Enumeration Type Documentation

4.1.3.1 enum rdc_status_t

Error codes returned by rocm_rdc_lib functions.

Enumerator

RDC_ST_OK Success.

RDC_ST_NOT_SUPPORTED Not supported feature.

RDC_ST_MSI_ERROR The MSI library error.

RDC_ST_FAIL_LOAD_MODULE Fail to load the library.

RDC_ST_INVALID_HANDLER Invalid handler.

RDC_ST_BAD_PARAMETER A parameter is invalid.

RDC_ST_NOT_FOUND Cannot find the value.

RDC_ST_CONFLICT Conflict with current state.

RDC_ST_CLIENT_ERROR The RDC client error.

RDC_ST_ALREADY_EXIST The item already exists.

RDC_ST_MAX_LIMIT Max limit recording for the object.

RDC_ST_INSUFF_RESOURCES Not enough resources to complete operation

RDC_ST_FILE_ERROR Failed to access a file.

RDC_ST_NO_DATA Data was requested, but none was found

RDC_ST_PERM_ERROR Insufficient permission to complete operation

RDC_ST_UNKNOWN_ERROR Unknown error.

4.1.3.2 enum rdc_group_type_t

type of GPU group

Enumerator

RDC_GROUP_DEFAULT All GPUs on the Node.

RDC_GROUP_EMPTY Empty group.

4.1.3.3 enum rdc_field_t

These enums are used to specify a particular field to be retrieved.

Enumerator

RDC_FI_INVALID Identifier fields. Invalid field value

RDC_FI_GPU_COUNT GPU count in the system.

RDC_FI_DEV_NAME Name of the device.

RDC_FI_GPU_CLOCK The current clock for the GPU.

RDC_FI_MEM_CLOCK Clock for the memory.

RDC_FI_MEMORY_TEMP Memory temperature for the device.

RDC_FI_GPU_TEMP Current temperature for the device.

RDC_FI_POWER_USAGE Power usage for the device.

RDC_FI_PCIE_TX PCIe Tx utilization information.

RDC_FI_PCIE_RX PCIe Rx utilization information.

RDC_FI_GPU_UTIL GPU Utilization.

RDC_FI_GPU_MEMORY_USAGE Memory usage of the GPU instance.

RDC_FI_GPU_MEMORY_TOTAL Total memory of the GPU instance.

RDC_FI_ECC_CORRECT_TOTAL ECC related fields. Accumulated correctable ECC errors

RDC_FI_ECC_UNCORRECT_TOTAL Accumulated uncorrectable ECC errors.

RDC_FI_ECC_SDMA_SEC SDMA Single Error Correction.

RDC_FI_ECC_SDMA_DED SDMA Double Error Detection.

RDC_FI_ECC_GFX_SEC GFX Single Error Correction.

RDC_FI_ECC_GFX_DED GFX Double Error Detection.

RDC_FI_ECC_MMHUB_SEC MMHUB Single Error Correction.

RDC_FI_ECC_MMHUB_DED MMHUB Double Error Detection.

RDC_FI_ECC_ATHUB_SEC ATHUB Single Error Correction.

RDC_FI_ECC_ATHUB_DED ATHUB Double Error Detection.

RDC_FI_ECC_BIF_SEC BIF Single Error Correction.

RDC_FI_ECC_BIF_DED BIF Double Error Detection.

RDC_FI_ECC_HDP_SEC HDP Single Error Correction.

RDC_FI_ECC_HDP_DED HDP Double Error Detection.

RDC_FI_ECC_XGMI_WAFL_SEC XGMI WAFL Single Error Correction.

RDC_FI_ECC_XGMI_WAFL_DED XGMI WAFL Double Error Detection.

RDC_FI_ECC_DF_SEC DF Single Error Correction.

RDC_FI_ECC_DF_DED DF Double Error Detection.

RDC_FI_ECC_SMN_SEC SMN Single Error Correction.

RDC_FI_ECC_SMN_DED SMN Double Error Detection.

RDC_FI_ECC_SEM_SEC SEM Single Error Correction.

RDC_FI_ECC_SEM_DED SEM Double Error Detection.

RDC_FI_ECC_MP0_SEC MP0 Single Error Correction.

RDC_FI_ECC_MP0_DED MP0 Double Error Detection.

RDC_FI_ECC_MP1_SEC MP1 Single Error Correction.

RDC_FI_ECC_MP1_DED MP1 Double Error Detection.

RDC_FI_ECC_FUSE_SEC FUSE Single Error Correction.

RDC_FI_ECC_FUSE_DED FUSE Double Error Detection.

RDC_FI_ECC_UMC_SEC UMC Single Error Correction.

RDC_FI_ECC_UMC_DED UMC Double Error Detection.

RDC_EVNT_XGMI_0_NOP_TX NOPs sent to neighbor 0.

RDC_EVNT_XGMI_0_REQ_TX Outgoing requests to neighbor 0

RDC_EVNT_XGMI_0_RESP_TX Outgoing responses to neighbor 0

RDC_EVNT_XGMI_0_BEATS_TX Data beats sent to neighbor 0; Each beat represents 32 bytes.

XGMI throughput can be calculated by multiplying a BEATS event such as `::RSMI_EVNT_XGMI_0_BEATS_TX` by 32 and dividing by the time for which event collection occurred, `::rsmi_counter_value_t.time_running` (which is in nanoseconds). To get bytes per second, multiply this value by 10^9 .

Throughput = BEATS/time_running * 10^9 (bytes/second)

RDC_EVNT_XGMI_1_NOP_TX NOPs sent to neighbor 1.

RDC_EVNT_XGMI_1_REQ_TX Outgoing requests to neighbor 1

RDC_EVNT_XGMI_1_RESP_TX Outgoing responses to neighbor 1

RDC_EVNT_XGMI_1_BEATS_TX Data beats sent to neighbor 1; Each beat represents 32 bytes

RDC_EVNT_XGMI_0_THRPUT Transmit throughput to XGMI neighbor 0 in bytes/sec

RDC_EVNT_XGMI_1_THRPUT Transmit throughput to XGMI neighbor 1 in bytes/sec

RDC_EVNT_XGMI_2_THRPUT Transmit throughput to XGMI neighbor 2 in bytes/sec

RDC_EVNT_XGMI_3_THRPUT Transmit throughput to XGMI neighbor 3 in bytes/sec

RDC_EVNT_XGMI_4_THRPUT Transmit throughput to XGMI neighbor 4 in bytes/sec

RDC_EVNT_XGMI_5_THRPUT Transmit throughput to XGMI neighbor 5 in bytes/sec

RDC_EVNT_NOTIF_VMFAULT VM page fault.

RDC_EVNT_NOTIF_THERMAL_THROTTLE Clock frequency has decreased due to temperature rise

RDC_EVNT_NOTIF_PRE_RESET GPU reset is about to occur.

RDC_EVNT_NOTIF_POST_RESET GPU reset just occurred.

4.1.3.4 enum rdc_diag_level_t

type of diagnostic level

Enumerator

RDC_DIAG_LVL_INVALID invalid level

RDC_DIAG_LVL_SHORT take a few seconds to run

RDC_DIAG_LVL_MED take less than 2 minutes to run

RDC_DIAG_LVL_LONG take up to 15 minutes to run

4.1.3.5 enum rdc_diag_result_t

type of diagnostic result

Enumerator

RDC_DIAG_RESULT_PASS The diagnostic test pass.

RDC_DIAG_RESULT_SKIP The diagnostic test skipped.

RDC_DIAG_RESULT_WARN The diagnostic test has warnings.

RDC_DIAG_RESULT_FAIL The diagnostic test fail.

4.1.3.6 enum rdc_diag_test_cases_t

The test cases to run.

Enumerator

RDC_DIAG_TEST_FIRST The diagnostic test pass.

RDC_DIAG_COMPUTE_QUEUE The Compute Queue is ready.

RDC_DIAG_SYS_MEM_CHECK Check System memory.

RDC_DIAG_NODE_TOPOLOGY Report node topology.

RDC_DIAG_GPU_PARAMETERS GPU parameters in range.

4.1.4 Function Documentation

4.1.4.1 rdc_status_t rdc_init (uint64_t init_flags)

Initialize ROCm RDC.

When called, this initializes internal data structures, including those corresponding to sources of information that RDC provides. This must be called before [rdc_start_embedded\(\)](#) or [rdc_connect\(\)](#)

Parameters

<i>in</i>	<i>init_flags</i>	init_flags Bit flags that tell RDC how to initialize.
-----------	-------------------	---

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.2 `rdc_status_t rdc_shutdown ()`

Shutdown ROCm RDC.

Do any necessary clean up.

4.1.4.3 `rdc_status_t rdc_start_embedded (rdc_operation_mode_t op_mode, rdc_handle_t * p_rdc_handle)`

Start embedded RDC agent within this process.

The RDC is loaded as library so that it does not require rdc daemon. In this mode, the user has to periodically call [rdc_field_update_all\(\)](#) when op_mode is RDC_OPERATION_MODE_MANUAL, which tells RDC to collect the stats.

Parameters

<i>in</i>	<i>op_mode</i>	Operation modes. When RDC_OPERATION_MODE_AUTO, RDC schedules background task to collect the stats. When RDC_OPERATION_MODE_MANUAL, the user needs to call rdc_field_update_all() periodically.
<i>in, out</i>	<i>p_rdc_handle</i>	Caller provided pointer to rdc_handle_t. Upon successful call, the value will contain the handler for following API calls.

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.4 `rdc_status_t rdc_stop_embedded (rdc_handle_t p_rdc_handle)`

Stop embedded RDC agent.

Stop the embedded RDC agent, and p_rdc_handle becomes invalid after this call.

Parameters

<i>in</i>	<i>p_rdc_handle</i>	The RDC handler that come from rdc_start_embedded() .
-----------	---------------------	---

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.5 `rdc_status_t rdc_connect (const char * ipAndPort, rdc_handle_t * p_rdc_handle, const char * root_ca, const char * client_cert, const char * client_key)`

Connect to rdc daemon.

This method is used to connect to a remote stand-alone rdc daemon.

Parameters

in	<i>ipAndPort</i>	The IP and port of the remote rdc. The ipAndPort can be specified in this x.x.x.x:yyyy format, where x.x.x.x is the IP address and yyyy is the port.
in, out	<i>p_rdc_handle</i>	Caller provided pointer to rdc_handle_t. Upon successful call, the value will contain the handler for following API calls.
in	<i>root_ca</i>	The root CA stored in the string in pem format. Set it as nullptr if the communication is not encrypted.
in	<i>client_cert</i>	The client certificate stored in the string in pem format. Set it as nullptr if the communication is not encrypted.
in	<i>client_key</i>	The client key stored in the string in pem format. Set it as nullptr if the communication is not encrypted.

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.6 `rdc_status_t rdc_disconnect (rdc_handle_t p_rdc_handle)`

Disconnect from rdc daemon.

Disconnect from rdc daemon, and p_rdc_handle becomes invalid after this call.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler that come from rdc_connect() .
----	---------------------	--

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.7 `rdc_status_t rdc_job_start_stats (rdc_handle_t p_rdc_handle, rdc_gpu_group_t group_id, const char job_id[64], uint64_t update_freq)`

Request the RDC to watch the job stats.

This should be executed as part of job prologue. The summary job stats can be retrieved using [rdc_job_get_stats\(\)](#). In RDC_OPERATION_MODE_MANUAL, user must call [rdc_field_update_all\(1\)](#) at least once, before call [rdc_job_get_stats\(\)](#)

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>group_id</i>	The group of GPUs to be watched.
in	<i>job_id</i>	The name of the job.
in	<i>update_freq</i>	How often to update this field in usec.

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.8 `rdc_status_t rdc_job_get_stats (rdc_handle_t p_rdc_handle, const char job_id[64], rdc_job_info_t * p_job_info)`

Get the stats of the job using the job id.

The stats can be retrieved at any point when the job is in process.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>job_id</i>	The name of the job.
in, out	<i>p_job_info</i>	Caller provided pointer to rdc_job_info_t . Upon successful call, the value will contain the stats of the job.

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.9 `rdc_status_t rdc_job_stop_stats (rdc_handle_t p_rdc_handle, const char job_id[64])`

Request RDC to stop watching the stats of the job.

This should be execute as part of job epilogue. The job Id remains available to view the stats at any point. You must call `rdc_watch_job_fields()` before this call.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>job_id</i>	The name of the job.

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.10 `rdc_status_t rdc_job_remove (rdc_handle_t p_rdc_handle, const char job_id[64])`

Request RDC to stop tracking the job given by `job_id`.

After this call, you will no longer be able to call [rdc_job_get_stats\(\)](#) on this `job_id`. But you will be able to reuse the `job_id` after this call.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>job_id</i>	The name of the job.

Return values

RDC_ST_OK	is returned upon successful call.
---------------------------	-----------------------------------

4.1.4.11 `rdc_status_t rdc_job_remove_all (rdc_handle_t p_rdc_handle)`

Request RDC to stop tracking all the jobs.

After this call, you will no longer be able to call [rdc_job_get_stats\(\)](#) on any job id. But you will be able to reuse the any previous used job id after this call.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
----	---------------------	------------------

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.12 `rdc_status_t rdc_field_update_all (rdc_handle_t p_rdc_handle, uint32_t wait_for_update)`

Request RDC to update all fields to be watched.

In RDC_OPERATION_MODE_MANUAL, the user must call this method periodically.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>wait_for_update</i>	Whether or not to wait for the update loop to complete before returning to the caller 1=wait. 0=do not wait.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.13 `rdc_status_t rdc_device_get_all (rdc_handle_t p_rdc_handle, uint32_t gpu_index_list[RDC_MAX_NUM_DEVICES], uint32_t * count)`

Get indexes corresponding to all the devices on the system.

Indexes represents RDC GPU Id corresponding to each GPU on the system and is immutable during the lifespan of the engine. The list should be queried again if the engine is restarted.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
out	<i>gpu_index_list</i>	Array reference to fill GPU indexes present on the system.
out	<i>count</i>	Number of GPUs returned in <i>gpu_index_list</i> .

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.14 `rdc_status_t rdc_device_get_attributes (rdc_handle_t p_rdc_handle, uint32_t gpu_index, rdc_device_attributes_t * p_rdc_attr)`

Gets device attributes corresponding to the *gpu_index*.

Fetch the attributes, such as device name, of a GPU.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>gpu_index</i>	GPU index corresponding to which the attributes should be fetched
out	<i>p_rdc_attr</i>	GPU attribute corresponding to the <i>gpu_index</i> .

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.15 `rdc_status_t rdc_group_gpu_create (rdc_handle_t p_rdc_handle, rdc_group_type_t type, const char * group_name, rdc_gpu_group_t * p_rdc_group_id)`

Create a group contains multiple GPUs.

This method can create a group contains multiple GPUs. Instead of executing an operation separately for each GPU, the RDC group enables the user to execute same operation on all the GPUs present in the group as a single API call.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>type</i>	The type of the group. RDC_GROUP_DEFAULT includes all the GPUs on the node, and RDC_GROUP_EMPTY creates an empty group.
in	<i>group_name</i>	The group name specified as NULL terminated C String
in, out	<i>p_rdc_group_id</i>	Caller provided pointer to rdc_gpu_group_t. Upon successful call, the value will contain the group id for following group API calls.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.16 `rdc_status_t rdc_group_gpu_add (rdc_handle_t p_rdc_handle, rdc_gpu_group_t group_id, uint32_t gpu_index)`

Add a GPU to the group.

This method can add a GPU to the group

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>group_id</i>	The group id to which the GPU will be added.
in	<i>gpu_index</i>	The GPU index to be added to the group.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.17 `rdc_status_t rdc_group_gpu_get_info (rdc_handle_t p_rdc_handle, rdc_gpu_group_t p_rdc_group_id, rdc_group_info_t * p_rdc_group_info)`

Get information about a GPU group.

Get detail information about a GPU group created by rdc_group_gpu_create

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>p_rdc_group_id</i>	The GPU group handler created by rdc_group_gpu_create
out	<i>p_rdc_group_info</i>	The information of the GPU group p_rdc_group_id.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.18 `rdc_status_t rdc_group_get_all_ids (rdc_handle_t p_rdc_handle, rdc_gpu_group_t group_id_list[], uint32_t * count)`

Used to get information about all GPU groups in the system.

Get the list of GPU group ids in the system.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
out	<i>group_id_list</i>	Array reference to fill GPU group ids in the system.
out	<i>count</i>	Number of GPU group returned in group_id_list.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.19 `rdc_status_t rdc_group_gpu_destroy (rdc_handle_t p_rdc_handle, rdc_gpu_group_t p_rdc_group_id)`

Destroy GPU group represented by p_rdc_group_id.

Delete the logic group represented by p_rdc_group_id

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>p_rdc_group_id</i>	The group id

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.20 `rdc_status_t rdc_group_field_create (rdc_handle_t p_rdc_handle, uint32_t num_field_ids, rdc_field_t * field_ids, const char * field_group_name, rdc_field_grp_t * rdc_field_group_id)`

create a group of fields

The user can create a group of fields and perform an operation on a group of fields at once.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>num_field_ids</i>	Number of field IDs that are being provided in field_ids.
in	<i>field_ids</i>	Field IDs to be added to the newly-created field group.
in	<i>field_group_name</i>	Unique name for this group of fields.
out	<i>rdc_field_group_id</i>	Handle to the newly-created field group

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.21 `rdc_status_t rdc_group_field_get_info (rdc_handle_t p_rdc_handle, rdc_field_grp_t rdc_field_group_id, rdc_field_group_info_t * field_group_info)`

Get information about a field group.

Get detail information about a field group created by rdc_group_field_create

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
----	---------------------	------------------

in	<i>rdc_field_group-_id</i>	The field group handler created by rdc_group_field_create
out	<i>field_group_info</i>	The information of the field group rdc_field_group_id.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.22 `rdc_status_t rdc_group_field_get_all_ids (rdc_handle_t p_rdc_handle, rdc_field_grp_t field_group_id_list[], uint32_t * count)`

Used to get information about all field groups in the system.

Get the list of field group ids in the system.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
out	<i>field_group_id_list</i>	Array reference to fill field group ids in the system.
out	<i>count</i>	Number of field group returned in field_group_id_list.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.23 `rdc_status_t rdc_group_field_destroy (rdc_handle_t p_rdc_handle, rdc_field_grp_t rdc_field_group_id)`

Destroy field group represented by rdc_field_group_id.

Delete the logic group represented by rdc_field_group_id

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>rdc_field_group-_id</i>	The field group id

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.24 `rdc_status_t rdc_field_watch (rdc_handle_t p_rdc_handle, rdc_gpu_group_t group_id, rdc_field_grp_t field_group_id, uint64_t update_freq, double max_keep_age, uint32_t max_keep_samples)`

Request the RDC start recording updates for a given field collection.

Note that the first update of the field will not occur until the next field update cycle. To force a field update cycle, user must call rdc_field_update_all(1)

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>group_id</i>	The group of GPUs to be watched.
in	<i>field_group_id</i>	The collection of fields to record

in	<i>update_freq</i>	How often to update fields in usec.
in	<i>max_keep_age</i>	How long to keep data for fields in seconds.
in	<i>max_keep_samples</i>	Maximum number of samples to keep. 0=no limit.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.25 **rdc_status_t** **rdc_field_get_latest_value** (**rdc_handle_t** *p_rdc_handle*, **uint32_t** *gpu_index*, **rdc_field_t** *field*, **rdc_field_value** * *value*)

Request a latest cached field of a GPU.

Note that the field can be cached after called **rdc_field_watch**

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>gpu_index</i>	The GPU index.
in	<i>field</i>	The field id
out	<i>value</i>	The field value got from cache.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.26 **rdc_status_t** **rdc_field_get_value_since** (**rdc_handle_t** *p_rdc_handle*, **uint32_t** *gpu_index*, **rdc_field_t** *field*, **uint64_t** *since_time_stamp*, **uint64_t** * *next_since_time_stamp*, **rdc_field_value** * *value*)

Request a history cached field of a GPU.

Note that the field can be cached after called **rdc_field_watch**

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>gpu_index</i>	The GPU index.
in	<i>field</i>	The field id
in	<i>since_time_stamp</i>	Timestamp to request values since in usec since 1970.
out	<i>next_since_time_stamp</i>	Timestamp to use for sinceTimestamp on next call to this function
out	<i>value</i>	The field value got from cache.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.27 **rdc_status_t** **rdc_field_unwatch** (**rdc_handle_t** *p_rdc_handle*, **rdc_gpu_group_t** *group_id*, **rdc_field_grp_t** *field_group_id*)

Stop record updates for a given field collection.

The cache of those fields will not be updated after this call

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>group_id</i>	The GPU group id.
in	<i>field_group_id</i>	The field group id.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.28 **rdc_status_t** rdc_diagnostic_run (**rdc_handle_t** *p_rdc_handle*, **rdc_gpu_group_t** *group_id*, **rdc_diag_level_t** *level*, **rdc_diag_response_t** * *response*)

Run the diagnostic test cases.

Run the diagnostic test cases at differenet levles.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>group_id</i>	The GPU group id.
in	<i>level</i>	The level decides how long the test will run. The RDC_DIAG_LVL_SHORT only take a few seconds, and the the RDC_DIAG_LVL_LONG may take up to 15 minutes.
in, out	<i>response</i>	The detail results of the tests run.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.29 **rdc_status_t** rdc_test_case_run (**rdc_handle_t** *p_rdc_handle*, **rdc_gpu_group_t** *group_id*, **rdc_diag_test_cases_t** *test_case*, **rdc_diag_test_result_t** * *result*)

Run one diagnostic test case.

Run a specific diagnostic test case.

Parameters

in	<i>p_rdc_handle</i>	The RDC handler.
in	<i>group_id</i>	The GPU group id.
in	<i>test_case</i>	The test case to run.
in, out	<i>result</i>	The results of the test.

Return values

<i>RDC_ST_OK</i>	is returned upon successful call.
----------------------------------	-----------------------------------

4.1.4.30 **const char*** rdc_status_string (**rdc_status_t** *status*)

Get a description of a provided RDC error status.

return the string in human readable format.

Parameters

<i>in</i>	<i>status</i>	The RDC status.
-----------	---------------	-----------------

Return values

<i>The</i>	string to describe the RDC status.
------------	------------------------------------

4.1.4.31 `const char* field_id_string (rdc_field_t field_id)`

Get the name of a field.

return the string in human readable format.

Parameters

<i>in</i>	<i>field_id</i>	The field id.
-----------	-----------------	---------------

Return values

<i>The</i>	string to describe the field.
------------	-------------------------------

4.1.4.32 `rdc_field_t get_field_id_from_name (const char * name)`

Get the field id from name.

return the field id from field name.

Parameters

<i>in</i>	<i>name</i>	The field name.
-----------	-------------	-----------------

Return values

<i>return</i>	RDC_FI_INVALID if the field name is invalid.
---------------	--

4.1.4.33 `const char* rdc_diagnostic_result_string (rdc_diag_result_t result)`

Get a description of a diagnostic result.

return the string in human readable format.

Parameters

<i>in</i>	<i>result</i>	The RDC diagnostic result.
-----------	---------------	----------------------------

Return values

<i>The</i>	string to describe the RDC diagnostic result.
------------	---

Index

entity_ids
 rdc_group_info_t, [10](#)

field_id_string
 rdc.h, [30](#)

field_ids
 rdc_field_group_info_t, [8](#)

get_field_id_from_name
 rdc.h, [30](#)

per_gpu_result_count
 rdc_diag_test_result_t, [7](#)

RDC_DIAG_COMPUTE_QUEUE
 rdc.h, [20](#)

RDC_DIAG_GPU_PARAMETERS
 rdc.h, [20](#)

RDC_DIAG_LVL_INVALID
 rdc.h, [20](#)

RDC_DIAG_LVL_LONG
 rdc.h, [20](#)

RDC_DIAG_LVL_MED
 rdc.h, [20](#)

RDC_DIAG_LVL_SHORT
 rdc.h, [20](#)

RDC_DIAG_NODE_TOPOLOGY
 rdc.h, [20](#)

RDC_DIAG_RESULT_FAIL
 rdc.h, [20](#)

RDC_DIAG_RESULT_PASS
 rdc.h, [20](#)

RDC_DIAG_RESULT_SKIP
 rdc.h, [20](#)

RDC_DIAG_RESULT_WARN
 rdc.h, [20](#)

RDC_DIAG_SYS_MEM_CHECK
 rdc.h, [20](#)

RDC_DIAG_TEST_FIRST
 rdc.h, [20](#)

RDC_EVNT_NOTIF_POST_RESET
 rdc.h, [20](#)

RDC_EVNT_NOTIF_PRE_RESET
 rdc.h, [20](#)

RDC_EVNT_NOTIF_THERMAL_THROTTLE
 rdc.h, [20](#)

RDC_EVNT_NOTIF_VMFault
 rdc.h, [20](#)

RDC_EVNT_XGMI_0_BEATS_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_0_NOP_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_0_REQ_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_0_RESP_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_0_THRPUT
 rdc.h, [20](#)

RDC_EVNT_XGMI_1_BEATS_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_1_NOP_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_1_REQ_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_1_RESP_TX
 rdc.h, [19](#)

RDC_EVNT_XGMI_1_THRPUT
 rdc.h, [20](#)

RDC_EVNT_XGMI_2_THRPUT
 rdc.h, [20](#)

RDC_EVNT_XGMI_3_THRPUT
 rdc.h, [20](#)

RDC_EVNT_XGMI_4_THRPUT
 rdc.h, [20](#)

RDC_EVNT_XGMI_5_THRPUT
 rdc.h, [20](#)

RDC_FI_DEV_NAME
 rdc.h, [18](#)

RDC_FI_ECC_ATHUB_DED
 rdc.h, [19](#)

RDC_FI_ECC_ATHUB_SEC
 rdc.h, [19](#)

RDC_FI_ECC_BIF_DED
 rdc.h, [19](#)

RDC_FI_ECC_BIF_SEC
 rdc.h, [19](#)

RDC_FI_ECC_CORRECT_TOTAL
 rdc.h, [19](#)

RDC_FI_ECC_DF_DED
 rdc.h, [19](#)

RDC_FI_ECC_DF_SEC
 rdc.h, [19](#)

RDC_FI_ECC_FUSE_DED
 rdc.h, [19](#)

RDC_FI_ECC_FUSE_SEC
 rdc.h, [19](#)

RDC_FI_ECC_GFX_DED
 rdc.h, [19](#)

RDC_FI_ECC_GFX_SEC

[rdc.h, 19](#)
[RDC_FI_ECC_HDP_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_HDP_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_MMHUB_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_MMHUB_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_MP0_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_MP0_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_MP1_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_MP1_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_SDMA_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_SDMA_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_SEM_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_SEM_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_SMN_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_SMN_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_UMC_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_UMC_SEC](#)
[rdc.h, 19](#)
[RDC_FI_ECC_UNCORRECT_TOTAL](#)
[rdc.h, 19](#)
[RDC_FI_ECC_XGMI_WAFL_DED](#)
[rdc.h, 19](#)
[RDC_FI_ECC_XGMI_WAFL_SEC](#)
[rdc.h, 19](#)
[RDC_FI_GPU_CLOCK](#)
[rdc.h, 18](#)
[RDC_FI_GPU_COUNT](#)
[rdc.h, 18](#)
[RDC_FI_GPU_MEMORY_TOTAL](#)
[rdc.h, 19](#)
[RDC_FI_GPU_MEMORY_USAGE](#)
[rdc.h, 19](#)
[RDC_FI_GPU_TEMP](#)
[rdc.h, 18](#)
[RDC_FI_GPU_UTIL](#)
[rdc.h, 19](#)
[RDC_FI_INVALID](#)
[rdc.h, 18](#)
[RDC_FI_MEM_CLOCK](#)
[rdc.h, 18](#)
[RDC_FI_MEMORY_TEMP](#)
[rdc.h, 18](#)
[RDC_FI_PCIE_RX](#)

[rdc.h, 18](#)
[RDC_FI_PCIE_TX](#)
[rdc.h, 18](#)
[RDC_FI_POWER_USAGE](#)
[rdc.h, 18](#)
[RDC_GROUP_DEFAULT](#)
[rdc.h, 18](#)
[RDC_GROUP_EMPTY](#)
[rdc.h, 18](#)
[RDC_ST_ALREADY_EXIST](#)
[rdc.h, 18](#)
[RDC_ST_BAD_PARAMETER](#)
[rdc.h, 18](#)
[RDC_ST_CLIENT_ERROR](#)
[rdc.h, 18](#)
[RDC_ST_CONFLICT](#)
[rdc.h, 18](#)
[RDC_ST_FAIL_LOAD_MODULE](#)
[rdc.h, 18](#)
[RDC_ST_FILE_ERROR](#)
[rdc.h, 18](#)
[RDC_ST_INSUFF_RESOURCES](#)
[rdc.h, 18](#)
[RDC_ST_INVALID_HANDLER](#)
[rdc.h, 18](#)
[RDC_ST_MAX_LIMIT](#)
[rdc.h, 18](#)
[RDC_ST_MSI_ERROR](#)
[rdc.h, 18](#)
[RDC_ST_NO_DATA](#)
[rdc.h, 18](#)
[RDC_ST_NOT_FOUND](#)
[rdc.h, 18](#)
[RDC_ST_NOT_SUPPORTED](#)
[rdc.h, 18](#)
[RDC_ST_OK](#)
[rdc.h, 18](#)
[RDC_ST_PERM_ERROR](#)
[rdc.h, 18](#)
[RDC_ST_UNKNOWN_ERROR](#)
[rdc.h, 18](#)
[rdc.h](#)
[RDC_DIAG_COMPUTE_QUEUE, 20](#)
[RDC_DIAG_GPU_PARAMETERS, 20](#)
[RDC_DIAG_LVL_INVALID, 20](#)
[RDC_DIAG_LVL_LONG, 20](#)
[RDC_DIAG_LVL_MED, 20](#)
[RDC_DIAG_LVL_SHORT, 20](#)
[RDC_DIAG_NODE_TOPOLOGY, 20](#)
[RDC_DIAG_RESULT_FAIL, 20](#)
[RDC_DIAG_RESULT_PASS, 20](#)
[RDC_DIAG_RESULT_SKIP, 20](#)
[RDC_DIAG_RESULT_WARN, 20](#)
[RDC_DIAG_SYS_MEM_CHECK, 20](#)
[RDC_DIAG_TEST_FIRST, 20](#)
[RDC_EVNT_NOTIF_POST_RESET, 20](#)
[RDC_EVNT_NOTIF_PRE_RESET, 20](#)
[RDC_EVNT_NOTIF_THERMAL_THROTTLE, 20](#)

[RDC_EVNT_NOTIF_VMFAULT](#), [20](#)
[RDC_EVNT_XGMI_0_BEATS_TX](#), [19](#)
[RDC_EVNT_XGMI_0_NOP_TX](#), [19](#)
[RDC_EVNT_XGMI_0_REQ_TX](#), [19](#)
[RDC_EVNT_XGMI_0_RESP_TX](#), [19](#)
[RDC_EVNT_XGMI_0_THRPUT](#), [20](#)
[RDC_EVNT_XGMI_1_BEATS_TX](#), [19](#)
[RDC_EVNT_XGMI_1_NOP_TX](#), [19](#)
[RDC_EVNT_XGMI_1_REQ_TX](#), [19](#)
[RDC_EVNT_XGMI_1_RESP_TX](#), [19](#)
[RDC_EVNT_XGMI_1_THRPUT](#), [20](#)
[RDC_EVNT_XGMI_2_THRPUT](#), [20](#)
[RDC_EVNT_XGMI_3_THRPUT](#), [20](#)
[RDC_EVNT_XGMI_4_THRPUT](#), [20](#)
[RDC_EVNT_XGMI_5_THRPUT](#), [20](#)
[RDC_FI_DEV_NAME](#), [18](#)
[RDC_FI_ECC_ATHUB_DED](#), [19](#)
[RDC_FI_ECC_ATHUB_SEC](#), [19](#)
[RDC_FI_ECC_BIF_DED](#), [19](#)
[RDC_FI_ECC_BIF_SEC](#), [19](#)
[RDC_FI_ECC_CORRECT_TOTAL](#), [19](#)
[RDC_FI_ECC_DF_DED](#), [19](#)
[RDC_FI_ECC_DF_SEC](#), [19](#)
[RDC_FI_ECC_FUSE_DED](#), [19](#)
[RDC_FI_ECC_FUSE_SEC](#), [19](#)
[RDC_FI_ECC_GFX_DED](#), [19](#)
[RDC_FI_ECC_GFX_SEC](#), [19](#)
[RDC_FI_ECC_HDP_DED](#), [19](#)
[RDC_FI_ECC_HDP_SEC](#), [19](#)
[RDC_FI_ECC_MMHUB_DED](#), [19](#)
[RDC_FI_ECC_MMHUB_SEC](#), [19](#)
[RDC_FI_ECC_MP0_DED](#), [19](#)
[RDC_FI_ECC_MP0_SEC](#), [19](#)
[RDC_FI_ECC_MP1_DED](#), [19](#)
[RDC_FI_ECC_MP1_SEC](#), [19](#)
[RDC_FI_ECC_SDMA_DED](#), [19](#)
[RDC_FI_ECC_SDMA_SEC](#), [19](#)
[RDC_FI_ECC_SEM_DED](#), [19](#)
[RDC_FI_ECC_SEM_SEC](#), [19](#)
[RDC_FI_ECC_SMN_DED](#), [19](#)
[RDC_FI_ECC_SMN_SEC](#), [19](#)
[RDC_FI_ECC_UMC_DED](#), [19](#)
[RDC_FI_ECC_UMC_SEC](#), [19](#)
[RDC_FI_ECC_UNCORRECT_TOTAL](#), [19](#)
[RDC_FI_ECC_XGMI_WAFL_DED](#), [19](#)
[RDC_FI_ECC_XGMI_WAFL_SEC](#), [19](#)
[RDC_FI_GPU_CLOCK](#), [18](#)
[RDC_FI_GPU_COUNT](#), [18](#)
[RDC_FI_GPU_MEMORY_TOTAL](#), [19](#)
[RDC_FI_GPU_MEMORY_USAGE](#), [19](#)
[RDC_FI_GPU_TEMP](#), [18](#)
[RDC_FI_GPU_UTIL](#), [19](#)
[RDC_FI_INVALID](#), [18](#)
[RDC_FI_MEM_CLOCK](#), [18](#)
[RDC_FI_MEMORY_TEMP](#), [18](#)
[RDC_FI_PCIE_RX](#), [18](#)
[RDC_FI_PCIE_TX](#), [18](#)
[RDC_FI_POWER_USAGE](#), [18](#)

[RDC_GROUP_DEFAULT](#), [18](#)
[RDC_GROUP_EMPTY](#), [18](#)
[RDC_ST_ALREADY_EXIST](#), [18](#)
[RDC_ST_BAD_PARAMETER](#), [18](#)
[RDC_ST_CLIENT_ERROR](#), [18](#)
[RDC_ST_CONFLICT](#), [18](#)
[RDC_ST_FAIL_LOAD_MODULE](#), [18](#)
[RDC_ST_FILE_ERROR](#), [18](#)
[RDC_ST_INSUFF_RESOURCES](#), [18](#)
[RDC_ST_INVALID_HANDLER](#), [18](#)
[RDC_ST_MAX_LIMIT](#), [18](#)
[RDC_ST_MSI_ERROR](#), [18](#)
[RDC_ST_NO_DATA](#), [18](#)
[RDC_ST_NOT_FOUND](#), [18](#)
[RDC_ST_NOT_SUPPORTED](#), [18](#)
[RDC_ST_OK](#), [18](#)
[RDC_ST_PERM_ERROR](#), [18](#)
[RDC_ST_UNKNOWN_ERROR](#), [18](#)
[rdc.h](#), [13](#)
[field_id_string](#), [30](#)
[get_field_id_from_name](#), [30](#)
[rdc_connect](#), [21](#)
[rdc_device_get_all](#), [24](#)
[rdc_device_get_attributes](#), [24](#)
[rdc_diag_level_t](#), [20](#)
[rdc_diag_result_t](#), [20](#)
[rdc_diag_test_cases_t](#), [20](#)
[rdc_diagnostic_result_string](#), [30](#)
[rdc_diagnostic_run](#), [29](#)
[rdc_disconnect](#), [22](#)
[rdc_field_get_latest_value](#), [28](#)
[rdc_field_get_value_since](#), [28](#)
[rdc_field_t](#), [18](#)
[rdc_field_unwatch](#), [28](#)
[rdc_field_update_all](#), [24](#)
[rdc_field_watch](#), [27](#)
[rdc_group_field_create](#), [26](#)
[rdc_group_field_destroy](#), [27](#)
[rdc_group_field_get_all_ids](#), [27](#)
[rdc_group_field_get_info](#), [26](#)
[rdc_group_get_all_ids](#), [25](#)
[rdc_group_gpu_add](#), [25](#)
[rdc_group_gpu_create](#), [24](#)
[rdc_group_gpu_destroy](#), [26](#)
[rdc_group_gpu_get_info](#), [25](#)
[rdc_group_type_t](#), [18](#)
[rdc_handle_t](#), [17](#)
[rdc_init](#), [20](#)
[rdc_job_get_stats](#), [22](#)
[rdc_job_remove](#), [23](#)
[rdc_job_remove_all](#), [23](#)
[rdc_job_start_stats](#), [22](#)
[rdc_job_stop_stats](#), [23](#)
[rdc_shutdown](#), [21](#)
[rdc_start_embedded](#), [21](#)
[rdc_status_string](#), [29](#)
[rdc_status_t](#), [18](#)
[rdc_stop_embedded](#), [21](#)

- rdc_test_case_run, [29](#)
- rdc_connect
 - rdc.h, [21](#)
- rdc_device_attributes_t, [5](#)
- rdc_device_get_all
 - rdc.h, [24](#)
- rdc_device_get_attributes
 - rdc.h, [24](#)
- rdc_diag_detail_t, [5](#)
- rdc_diag_level_t
 - rdc.h, [20](#)
- rdc_diag_per_gpu_result_t, [6](#)
- rdc_diag_response_t, [6](#)
- rdc_diag_result_t
 - rdc.h, [20](#)
- rdc_diag_test_cases_t
 - rdc.h, [20](#)
- rdc_diag_test_result_t, [6](#)
 - per_gpu_result_count, [7](#)
- rdc_diagnostic_result_string
 - rdc.h, [30](#)
- rdc_diagnostic_run
 - rdc.h, [29](#)
- rdc_disconnect
 - rdc.h, [22](#)
- rdc_field_get_latest_value
 - rdc.h, [28](#)
- rdc_field_get_value_since
 - rdc.h, [28](#)
- rdc_field_group_info_t, [7](#)
 - field_ids, [8](#)
- rdc_field_t
 - rdc.h, [18](#)
- rdc_field_unwatch
 - rdc.h, [28](#)
- rdc_field_update_all
 - rdc.h, [24](#)
- rdc_field_value, [8](#)
 - value, [8](#)
- rdc_field_value_data, [8](#)
- rdc_field_watch
 - rdc.h, [27](#)
- rdc_gpu_usage_info_t, [9](#)
- rdc_group_field_create
 - rdc.h, [26](#)
- rdc_group_field_destroy
 - rdc.h, [27](#)
- rdc_group_field_get_all_ids
 - rdc.h, [27](#)
- rdc_group_field_get_info
 - rdc.h, [26](#)
- rdc_group_get_all_ids
 - rdc.h, [25](#)
- rdc_group_gpu_add
 - rdc.h, [25](#)
- rdc_group_gpu_create
 - rdc.h, [24](#)
- rdc_group_gpu_destroy
 - rdc.h, [26](#)
- rdc_group_gpu_get_info
 - rdc.h, [25](#)
- rdc_group_info_t, [10](#)
 - entity_ids, [10](#)
- rdc_group_type_t
 - rdc.h, [18](#)
- rdc_handle_t
 - rdc.h, [17](#)
- rdc_init
 - rdc.h, [20](#)
- rdc_job_get_stats
 - rdc.h, [22](#)
- rdc_job_group_info_t, [10](#)
- rdc_job_info_t, [11](#)
 - summary, [11](#)
- rdc_job_remove
 - rdc.h, [23](#)
- rdc_job_remove_all
 - rdc.h, [23](#)
- rdc_job_start_stats
 - rdc.h, [22](#)
- rdc_job_stop_stats
 - rdc.h, [23](#)
- rdc_shutdown
 - rdc.h, [21](#)
- rdc_start_embedded
 - rdc.h, [21](#)
- rdc_stats_summary_t, [11](#)
- rdc_status_string
 - rdc.h, [29](#)
- rdc_status_t
 - rdc.h, [18](#)
- rdc_stop_embedded
 - rdc.h, [21](#)
- rdc_test_case_run
 - rdc.h, [29](#)
- summary
 - rdc_job_info_t, [11](#)
- value
 - rdc_field_value, [8](#)